



SHEET METAL CONNECTORS, INC.

FABRICATION THAT PERFORMS

MINNEAPOLIS, MN
 5850 Main Street N.E.
 Minneapolis, Minnesota 55432
 LOCALLY CALL: 763-572-0000
 TOLL FREE: 1-800-328-1966
 FAX: 763-572-1100

ROCKFORD, IL
 5601 Sandy Hollow Road
 Rockford, Illinois 61109
 LOCALLY CALL: 815-874-4600
 TOLL FREE: 1-866-504-4600
 FAX: 815-874-9979



www.smcdct.com

Reducers with E-Z Flange

SMC spiral fittings are manufactured with an elbow lock seam, lap seam (i.e. stitch weld, riveted, tack weld or solid weld), standing seam or butt weld seam. These may be with or without duct sealant.


All fittings can be manufactured with:

- E-Z Flange Jr. with Barrel Clamp - 6" to 24" Diameter
- E-Z Flange with Barrel Clamp - 26" to 96" Diameter



Concentric Reducer

Dimensions to be listed as follows: A, B
 LR = See Chart




Standard Lengths for Concentric Reducers (LR)

30																		31	31	28	25	23	20	17	14	12	10									
28																		28	28	25	23	20	17	14	12	10										
26																	28	25	24	23	21	20	17	14	12	10										
24																	28	25	24	23	21	20	17	14	12	10										
22																		25	24	23	21	20	19	17	14	12	10									
20																		23	21	20	19	17	16	14	13	10										
18																		21	20	19	17	16	14	13	12	10										
16																		20	19	17	16	14	13	12	10	10										
14																		19	17	16	14	13	12	10	10	9										
13																		20	19	17	16	14	13	12	10	10	9									
12																		19	17	16	14	13	12	10	10	9										
11																		17	16	14	13	12	10	10	9	9										
10																		16	14	13	12	10	10	10	9	9										
9																		14	13	12	10	10	9	9	9	9										
8																		13	12	10	10	9	9	9	9	9										
7																		13	10	10	9	9	9	9	9	9										
6																																				
5																																				
4																																				
3																																				
																		3	4	5	6	7	8	9	10	11	12	13	14	16	18	20	22	24	26	28



Eccentric Reducer

Dimensions to be listed as follows: A,B
 LR = See Chart



Size Reduction	LR
1" reduction	8 1/2"
2" reduction	11"
3" reduction	13 1/2"
4" reduction	16"
5" reduction	18 1/2"
6" reduction	21"
7" reduction	23 1/2"
8" reduction	26"
9" reduction	28 1/2"
10" reduction	31"
11" reduction	33 1/2"
12" reduction	36"
14" reduction	41"
16" reduction	46"
18" reduction	51"
20" reduction	56"

